

**Texas Instruments Engineering Evaluation Units versus MIL-PRF-38535 QML Class V Processing**

Texas Instruments Engineering Evaluation (/EM and -MPR) samples are intended for engineering evaluation only. While using the same die as fully qualified and processed space-grade products (QML Class V or TI -MLS), they are processed to a non-compliant flow (for example, no burn-in, and so forth) and are tested to a temperature rating of +25°C only. These units are not suitable for qualification, production, radiation testing or flight use. Parts are not specified for performance over the full military specified temperature range of –55°C to +125°C or for operating life.

Processing Step	MIL-PRF-38535 QML Class V	Engineering Evaluation Units
<ul style="list-style-type: none"> <li>• <i>Qualified Production Facilities and Material Set</i> <ul style="list-style-type: none"> <li>○ <i>QML V Qualified Die and Wafer Fab</i></li> <li>○ <i>QML V Qualified Assembly Site</i></li> <li>○ <i>Qualified Hermetic Package With Class V Material Set (Die Attach, Bondwire, Lid Seal)</i></li> </ul> </li> </ul>	Yes	Yes
• <i>Wafer Lot Acceptance</i>	Yes	Optional
• <i>Pre-Seal Visual Inspection – Condition A</i>	100% at 100X and 40X	No
• <i>Pre-Seal Visual Lot Acceptance- Condition A</i>	45(0) at 100X and 40X	40X only
• <i>Temperature Cycle</i>	Yes	No
• <i>Centrifuge</i>	Yes	No
• <i>Particle Impact Noise Detection (PIND)</i>	Yes	No
• <i>X-Ray (Radiography)</i>	Yes	No
• <i>Pre Burn-in +25°C Electrical Test</i>	Yes	No
• <i>Burn-In +125°C for 240 Hours or equivalent</i>	Yes	No
• <i>+25°C Electrical Test</i>	Yes	Yes
• <i>PDA Calculations</i>	Yes	No
• <i>+25°C Group A Lot Acceptance</i>	116(0)	No
• <i>+125°C Electrical Test</i>	Yes	No
• <i>+125°C Group A Lot Acceptance</i>	116(0)	No
• <i>-55°C Electrical Test</i>	Yes	No
• <i>-55°C Group A Lot Acceptance</i>	116(0)	No
• <i>Hermeticity – Fine Leak</i>	Yes	Yes
• <i>Hermeticity – Gross Leak</i>	Yes	Yes
• <i>External Visual Inspection</i>	Yes	No
• <i>External Visual Lot Acceptance</i>	45(0)	45(0)
• <i>Quality Conformance Inspection</i>	Yes	No
• <i>Processing Conformance Report / QCI Summaries</i>	Yes	No

For more information please contact the TI Customer Support Center at [www.ti.com/csc](http://www.ti.com/csc) or your local TI representative.

*THIS INFORMATION IS PROVIDED STRICTLY "AS IS." TI warrants that its products conform to the official published Specifications for such products, in accordance with TI's Terms of Sale at the following link: [www.ti.com/termsofsale](http://www.ti.com/termsofsale) Use of TI products outside limits stated in those Specifications is entirely at the customer's risk, and will void the warranty if such misuse causes the part not to work. This information could change without notice. TI makes no warranties and assumes no liability for applications assistance or customer product design. Customers are solely responsible to conduct sufficient engineering and additional qualification testing to determine whether a candidate device is suitable for use in their applications.*

## **IMPORTANT NOTICE AND DISCLAIMER**

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](http://ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265

Copyright © 2023, Texas Instruments Incorporated

## IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2023, Texas Instruments Incorporated