


Efficiency


The efficiency of the converter is shown below:




Ripple and Noise

Ripple measurements taken with a 48V input, 7.2A load, and 20MHz BWL.

Output Ripple (J4)
 10mV/div, 2usec/div
 Measured 26.3mVpp:



Input Ripple (C9)
 50mV/div, 2usec/div
 Measured 184mVpp:




Dynamic Loading


Output Load Step, 3A to 6A
 Slew rate = 200mA/usec
 200mV/div, 200usec/div

Output Load Step, 6A to 7.2A
 Slew rate = 200mA/usec
 200mV/div, 500usec/div


Measured 438mVpp:



Measured 338mVpp:




Output Load Step, 6A to 8.5A
 Slew rate = 200mA/usec
 200mV/div, 200usec/div
 Measured 363mVpp:




Turn On Response

Output, 7.2A Load, 1msec/div:




Output, 0A Load, 1msec.div:




Stability (Loop Gain)

The figure below is the loop gain of the converter with a 48V input and 6A load. The Bandwidth is 4.4 KHz, the Phase Margin is 56 degrees, and the Gain Margin is 18 dB.




Photo



Thermal Plot

Thermal profile of the board with a 48V input and 7.2A load:



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (<https://www.ti.com/legal/termsofsale.html>) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2021, Texas Instruments Incorporated