



P.O. Box 84
 Sherman, TX 75090
 6412 Hwy 75 South
 Sherman, TX 75090

(903) 868-7111

Texas Instruments Extended Temperature Products Reliability Report

(Subject To Attached Disclaimers)

Device Type/Device Family: INA128HD
 Package Type: 8/D
 Wafer Fabrication Facility: HFAB/SFAB
 Assembly/Test Facility: MLA
 Compiled: 03/12

Biased Life Test

Test Method: JESD22-A108
 Test Condition: 175C/1000 hours or equivalent 45/0 Minimum Sample
 Sample Size: 45
 Rejects: 0

Package Sequence Test

<u>Description</u>	<u>Condition</u>	<u>Referenced Method</u>	<u>Lot/Sample</u>	<u>Rejects</u>
Preconditioning		QSS009-142 JEDEC Std. 22 Method A112/A113	3/45	0
CSAM/TSAM Exposed pad devices only	No Delamination		3/45	0
Storage Bake	2000hr @ Data Sheet Operating Temperature		3/45	N/A
Temperature Cycle	-65°C to +150°C non-biased for 500 cycles or equivalent	JESD22-A104-A	3/45	N/A
Electrical Test	Per Data Sheet with Additional Pin to Pin Leakage Testing		3/45	0
CSAM	No Delamination on Lead or Die		3/5	0
TSAM Exposed pad devices only	50% Maximum Mount Pad Delamination		3/5	0
Decap/Bond Pull	Wirebond Packages Only		3/5-15 Wires	0
Decap/Bond Shear	Wirebond Packages Only	ASTM F-459	3/5-15 Wires	0
Cross Section	Through ball bond or flip chip bump	Examine for bond Integrity	3/1	0

Additional Qualification Testing

The subject Enhanced Plastic device, device family, and/or package family have passed Texas Instruments product qualification as follows:

<u>Description</u>	<u>Condition</u>	<u>Referenced Method</u>	<u>Sample Size</u>	
Electrical Characterization	TI Data Sheet	N/A	30 Units	
Electrostatic Discharge Sensitivity	HBM	EIA/JESD22-A114	3 Units/voltage	
	MM	EIA/JESD22-A115	N/A	
	CDM	JESD22-C101	N/A	
Latch-up	Per Technology	EIA/JESD78	6/0	
Physical Dimensions	TI Data Sheet	EIA/JESD22- B100	15/0	
Thermal Impedance	Theta-JA on board	EIA/JESD51	Per Pin-Package	
Bias Life Test	125°C / 1000 hours or equivalent	JESD22-A108	77/0	
Biased Humidity or HAST	85°C / 85% / 1000 hours	JESD22-A101	77/0	*
	130°C / 85% / 96 hours	JESD22-A110		
Autoclave or Unbiased HAST	121°C @ 2 atm / 96 hours	JESD22-A102	77/0	*
	130°C / 85% / 96 hours	JESD22-A110		
Temperature Cycle	-65°C to +150°C non-biased for 500 cycles or equivalent	JESD22-A104	77/0	*
Solderability	Condition A (steam age for 8 hours)	ANSI/J-STD-002-92	22/0	
Bond Strength	-	ASTM F-459	30/0	
Moisture Sensitivity	Surface Mount Only	J-STD-020-A	12/0	

* Preconditioning per JEDEC Std. 22, Method A112/A113

Supplemental Device Characteristics

Master Die: FINA128EP	Assembly Site: MLA
Wafer Fab: HFAB/SFAB	Pin/Package Type: 8/D
Fab Process: SFAB	Lead Composition: Cu
Fab Technology: LIN-40V-1 (JI1)	Lead Finish: NiPdAu
Die Revision: E	Packaged Die Thickness: .2794mm
Passivation: 5KA SiO ₂ /8KA SiON	MSL Level: 3/260C
Metal 1: 11kA AlCu0.5%	Metal 4: N/A
Metal 2: N/A	Metal 5: N/A
Metal 3: N/A	Metal 6: N/A

Quality and Reliability Data Disclaimer

The attached quality and reliability information is specific to the TI HT Plastic product family of plastic encapsulated commercial-off-the-shelf (COTS) semiconductor products and components. Due to possible differences in product assembly and test baselines, this information is NOT APPLICABLE to TI standard, industrial, or automotive catalog commercial products.

Plastic encapsulated TI semiconductor devices are not designed and are not warranted to be suitable for use in some military applications and/or military environments. Use of plastic encapsulated TI semiconductor devices in military applications and/or military environments, in lieu of hermetically sealed ceramic devices, is understood to be fully at the risk of Buyer.

Quality and reliability data provided by Texas Instruments is intended to be an estimate of product performance based upon history only. It does not imply that any performance levels reflected in such data can be met if the product is operated outside the conditions expressly stated in the latest published data sheet for a device.

Existing industry standards for plastic encapsulated microcircuit qualification and reliability monitors are based upon historical data, experiments, and field experience with the use of these devices in commercial and industrial applications. The applicability of these standards in determining the suitability for use and safety performance in military and aerospace applications has not been established. Due to the multiple variations in field operating conditions, a component manufacturer can only base estimates of product life on models and the results of package and die level qualification.

The buyer's use of this data, and all consequences of such use, is solely the buyer's responsibility. Buyer assumes full responsibility to perform sufficient engineering and additional qualification testing in order to properly evaluate the buyer's application and determine whether a candidate device is suitable for use in that application. The information provided by TI shall not be considered sufficient grounds on which to base any such determination.

THIS INFORMATION IS PROVIDED "AS IS" WITHOUT ANY EXPRESS OR IMPLIED WARRANTY OF ANY KIND INCLUDING WARRANTIES OF MERCHANTABILITY, NONINFRINGEMENT OF INTELLECTUAL PROPERTY, OR FITNESS FOR ANY PARTICULAR PURPOSE. IN NO EVENT SHALL TI OR ITS SUPPLIERS BE LIABLE FOR ANY DAMAGES WHATSOEVER (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION, LOSS OF INFORMATION) ARISING OUT OF THE USE OF OR INABILITY TO USE THE INFORMATION, EVEN IF TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

THIS INFORMATION SHOULD NOT BE USED TO ASSIST IN THE PRACTICE OF "UPRATING" OR "UPSCREENING" DEVICES FOR USE BEYOND THEIR RATED LIMITS.

TI may provide technical, applications or design advice, quality characterization, and reliability data or service providing these items shall not expand or otherwise affect TI's warranties as set forth in the Texas Instruments Incorporated Standard Terms and Conditions of Sale for Semiconductor Products and no obligation or liability shall arise from TI's provision of such items.

Quality and Reliability Data copyright © 2011, Texas Instruments Incorporated, all rights reserved.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46C and to discontinue any product or service per JESD48B. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components which meet ISO/TS16949 requirements, mainly for automotive use. Components which have not been so designated are neither designed nor intended for automotive use; and TI will not be responsible for any failure of such components to meet such requirements.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community e2e.ti.com